



AX-572

AX-572 Ψηφιακό πολύμετρο LCD 3,5 ψηφίων με καπασιτομετρο 20mF

- Measurement: transistors' gain hFE, AC voltage, DC voltage, capacitance, AC current, DC current, resistance
- Sampling: 3x/s
- DC voltage measuring range: 100^μ...200m/2/20/200/1000V
- DC voltage measuring accuracy: ±(0,5% + 3 digits)
- AC voltage measuring range: 1m...2/20/200/750V
- AC voltage measuring accuracy: ±(2% + 5 digits)
- DC current measuring range: 0,01^μ...20^μ/2m/200m/20A
- DC current measuring accuracy: ±(0,8% + 10 digits)
- AC current measuring range: 1^μ...2m/200m/20A
- AC current measuring accuracy: ±(0,8% + 5 digits)
- Resistance measuring range: 0,1...200/2k/20k/200k/2M/20MΩ
- Resistance measuring accuracy: ±(0,8% + 3 digits)
- Capacitance measuring range: 20mF
- Capacitance measuring accuracy: ±(2,5% + 20 digits)
- Diode test: 1mA, 3V
- Transistors' gain: (hFE) test 3V
- Continuity test: acoustic signal for R up to 70Ω
- Overall dimensions (W x D x H): 93x55x175mm
- Weight: 400g
- Power supply: 1 battery 9V 6F22, set without battery
- Conform to the norm: EN61010 600V CAT III